



ONIKUMA

MT603

■ Keyboard specifications

Number of keys: 68

Switch type: Customized linear axis-lubricated

Key life: 50 million times

Operation stroke: 3.6±0.3mm

Operation load: 47±5gf

Cable length: PVC3.5*1.5M

Keyboard size: 322.8*117.2*36mm

Supported systems: Win10, Win11, Android,

Mac and other operating systems

Keyboard weight: 656±5g

Working voltage: 5V±0.5V

Battery capacity: 3000mAh

Charging time: 4H

Battery life: 15H

Working current: <220mA

Interface type: TYPE-C

■ Combination functions of keys

FN+	Q	Short press to switch wireless 1, long press wireless 1 pairing	After dialing BT, press FN+Q/W/E to enter wireless mode. Press and hold the FN+Q/W/E key combination for 3 seconds, the keyboard enters pairing mode, the blue/green/red indicator light flashes quickly, and the indicator light stays on for 3 seconds after connecting. After failing to find a paired device for 30 seconds, exit pairing mode, the light goes out, and the keyboard goes to sleep.
	W	Short press to switch wireless 2, long press wireless 2 pairing	
	E	Short press to switch wireless 3, long press wireless 3 pairing	
	R	Short press to switch 2.4G, long press 2.4G pairing	After the keyboard dials 2.4G, press FN+R to enter 2.4G mode, and then press the FN+R key combination for 3S to enter pairing mode, insert the receiver, the indicator light flashes quickly, and after pairing is successful, the pairing mode light stays on for 3S. After 30s of not finding a paired device, the light goes out when the keyboard exits the pairing mode, and the keyboard goes to sleep.

FN+

Combination key	WIN function	MAC function (single press trigger)
1!	F1	Screen brightness down
2@	F2	Screen brightness up
3#	F3	Multitasking controller
4\$	F4	Program list
5%	F5	None
6^	F6	None
7&	F7	Previous song
8*	F8	Play/Pause
9(	F9	Next song
0)	F10	Mute
- _	F11	Volume down
= +	F12	Volume up
INS	End	End
DEL	HOME	HOME
PGUP	PrtSc	PrtSc
PGDN	Pause	Pause
ECS	` ~	
Y	One-click access to the web driver	
TAB	Switch to wired mode	
BACKSPAC	长按3S 恢复出厂设置	

■ Lighting control

FN+		Keyboard backlight color switch	(sequence: colorful, red, orange, yellow, green, cyan, blue, purple, white)
	Enter	Keyboard backlight effect switch	19 lighting effects, default to follow the flow
	Space	Check battery power (battery power supply is valid in wireless mode)	Press the combination key Fn+Space, the backlight turns off, and the number keys 1 to 0 light up to show the battery percentage. For example: 1 lights up, indicating 10% battery, 1 and 2 lights up, indicating 20% battery. And so on. (Red below 30%, yellow below 50%, green above 50%).
	T	Keyboard backlight switch	With memory
	WIN-L	Lock WIN	Win will light up white
	   	Light speed increases Light speed decreases Light brightness + Light brightness -	When in the limit gear, the up, down, left, and right lights flash 3 times to indicate.

■ Switch indication description



ON: Power on

OFF: Power off

CAPS indicator: CAPS key illuminates white

Win lock indicator: WIN key illuminates white

FN+A (Windows)

FN+S (Mac)

“Information to User”

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation.

Important: Change or modifications not expressly approved by the manufacturer responsible for compliance could void the user's authority to operate the equipment.