

Έξυπνος λαμπτήρας οροφής με φωτισμό άκρων

Yeelight Mars C300

YEELIGHT · EAN 6924922260691

Machine translation from Čeština. In case of doubt the manufacturer's original document prevails.

Yeelight RGB Smart Ceiling

Light Mars C300

User Manual

PL

Product Description

Mounting Plate

Steel Wire

Connection Box

Luminaire Body

Screws Expansion Remote Control

Self-drilling *3 Sleeves *3 *1

Accessory List

11

PL

Installation Steps

1. Remove the expansion plugs from the accessory kit and separate the mounting plate from the luminaire body. 2. Determine the installation location, drill holes according to the holes in the mounting plate, and use the expansion plugs to secure the mounting plate. Before installation, ensure that the power is turned off to avoid electric shock.

12

PL

3. After confirming that the mounting plate is stable, hang the safety cable of the lamp body on the mounting plate's hook. *After completing the installation, ensure that the device is stable to prevent it from falling. 4. Remove the cover and connect the wiring; cover the cap after completing the connections, ensuring that the power is off before plugging in the wires.

13

PL

5. Center the release arrow on the lamp body with the alignment arrow on the mounting plate, rotate until the safety arrow on the lamp body aligns with the positioning hole on the mounting plate, and you will hear a sound confirming correct installation; turn on the power.

Tighten

14

PL

Remote Control Instructions

OFF Button

ON Button

Brightness +

Color Temperature \ Color Button

Brightness -

M Button

Pairing: Within 1 minute of turning on the power, simultaneously press the OFF + M buttons on the remote; the indicator on the remote will start blinking, indicating that pairing is in progress, wait for the controlled lamp to blink, confirming successful pairing. ON Button: A short press turns on the light, a long press activates ambient lighting. OFF Button: A short press turns off the light, a long press deactivates ambient lighting. Color Temperature \ Color Button: a. A short press controls the main light b. A long press controls ambient lighting: i. Switches colors. M Button: a. A short press switches: Main light Daylight / Moonlight / Color / Flow mode b. A long press switches: Ambient light – solid color and smooth color transition effects Brightness +: a. A short press increases the brightness of the main light, b. A long press increases the brightness of the ambient light + Brightness -: a. Short press for the main light and brightness - b. Long press for ambient light brightness

15

PL

Factory Reset

Reset by turning the switch on and off five times (turn on for 2 seconds, turn off for 2 seconds), the light will start breathing and automatically restart. This restores factory settings. Neutral light 4000K/100% brightness with five breaths indicates a successful reset and allows for new pairing. If the luminaire is used in a new network environment, it is necessary to restore factory settings and reconnect to the network. Specifications

Model: YLXDD-0266

Power Factor: $\geq$ 0.6

Operating Temperature: -20 to +45 °C

Operating Humidity: 0 %–75 % RH

Color Temperature: 2700–6500 K

Rated Voltage: 200–240 V□

Rated Power: Lamp Power: 24 W

Compatible with: Android 4.4 or iOS 10.1 and newer versions

Wireless Connection: Wi-Fi IEEE 802.11b/g/n 2.4 GHz, BLE4.1 or higher

Operating Frequency: 50/60 Hz

This product contains a light source of energy efficiency class <D>. Replaceable light source (LED only) by a professional only. Safety Precautions

Before use, ensure that the voltage matches the operating voltage of the ceiling luminaire. Using incorrect voltage may damage the ceiling luminaire and pose a safety risk. Do not replace the light source of the ceiling luminaire yourself. The light source should only be replaced by the manufacturer, service department, or qualified electrician. The ceiling luminaire generates heat during operation. Ensure it is well-ventilated for heat dissipation. This ceiling luminaire can be controlled via an app or remote control (not included in the packaging, sold separately). Turning off the ceiling luminaire using the remote control or app does not disconnect it from the power supply; do not touch, replace, or disassemble this luminaire. Otherwise, there is a risk of electric shock, injury, or even death.

16

PL

Installation of the luminaire requires a qualified electrician, and the wiring must comply with IEEE standards or national electrical codes. The ceiling luminaire must be installed in a stable location to prevent it from falling. Under normal usage conditions, a distance of at least 19 cm should be maintained between the antenna and the user's body. For indoor use only. The light source in this luminaire can only be replaced by the manufacturer, service technician, or a person with appropriate qualifications.

WARNING

Please handle with care and keep away from open flames. EU Declaration of Conformity
Qingdao Yeelink Information Technology Co., Ltd. hereby declares that the type of radio equipment YLXDD-0267 is in compliance with Directive 2014/52/EU.

Disposal and Recycling of WEEE

All products marked with this symbol are waste electrical and electronic equipment (WEEE) according to Directive 2012/18/EU, which should not be mixed with other waste; it is necessary to designate collection points for the recycling of waste electrical and electronic

equipment established by the state or local authorities. Proper disposal and recycling will help prevent potential negative impacts on the environment and human health. Contact an installer or local authorities for more information about the location and conditions of collection points.

PL

Connect to the Mi Home app

Download the app

Search for 'Mi Home' in the app store or scan the QR code to download and install the app.

Add device

· Go to the main page of the Mi Home app, click on '+' in the upper right corner to add a device. · Follow the instructions in the app to complete the configuration. · After successfully adding the device, you will find it in the device list. About 'cooperation with Xiaomi Home' 'Cooperation with Xiaomi Home' means that the product is designed to connect and cooperate with the Xiaomi Home app. Please note that the certification only applies to interaction with the app. Xiaomi and Mijia are not responsible for the manufacturing, safety standards, or quality control of the product. Note: actual operation may vary due to app updates. Follow the instructions in the app.

Factory Reset

Use the wall switch to turn the ceiling light on and off five times in a row (turn off the ceiling light and wait two seconds, then turn it on and wait another two seconds, which counts as one cycle). The ceiling light will start breathing and will restart after five seconds, restoring factory settings. Warning: When using the ceiling light in a new network environment, it is necessary to restore factory settings and reconnect it to the network.

PL

Specifications

Model: YLXDD-0267

Power factor: 0.9

Operating temperature: -20 to +45°C

Operating humidity: 0 %-75 % RH

Color temperature: 2700-6500 K

Rated voltage: 220-240V□

Rated power: Lamp power: 30 W

Scan the QR code for more instructions

Compatible with: Android 4.4 or iOS 10.1 and newer versions

Wireless connection: Wi-Fi IEEE 802.11b/g/n 2.4 GHz, BLE4.1 or higher

Operating frequency: 50/60 Hz

This product contains a light source of energy efficiency class <D>. Replaceable light source (LED only) by a professional. WARNING

Please handle with care and keep away from open flames. EU Declaration of Conformity
Qingdao Yeelink Information Technology Co., Ltd. hereby declares that the type of radio equipment YLXDD-0267 is in compliance with Directive 2014/52/EU. Disposal and Recycling of WEEE

All products marked with this symbol are waste electrical and electronic equipment (WEEE) according to Directive 2012/18/EU, which should not be mixed with other waste; it is necessary to designate collection points for the recycling of waste electrical and electronic equipment established by the state or local authorities. Proper disposal and recycling will help prevent potential negative impacts on the environment and human health. Contact an installer or local authorities for more information about the location and conditions of collection points.

19

Manufacturer: Qingdao Yeelink Information Technology Manufacturer: Qingdao Yeelink Information Technology

Limited Liability Company Limited Liability Company

Address: 10F-B4, Building B, Qingdao International In- Address: 10F-B4, Building B, Qingdao International

novation Park, No. 1 Keyuan Weiyi Road, Laoshan District, Innovation Park, No. 1 Keyuan Weiyi Road, Laoshan District,

Qingdao City, Shandong Province, China Qingdao City, Shandong Province, China

Website: en.yeelight.com

Customer service: support@yeelight.com

This document is a translation of the original user manual created by the manufacturer.

Detailed information about the warranty conditions of the distributor/manufacturer is available on the website <https://serwis.innpro.pl/gwarancja>

The product must be regularly maintained (cleaned) by the user or a specialized service center at the user's expense. If the user manual does not provide information about necessary periodic maintenance or service actions, the physical condition of the product must be assessed regularly, at least once a week, for deviations from that of a physically new product. If any deviation is detected or found, maintenance (cleaning) or service measures must be carried out immediately. If proper maintenance (cleaning) is not performed and no action is taken in response to the identified different condition, permanent

damage to the product may occur. The guarantor is not responsible for damages resulting from negligence.

Warnings and Safety Information

All information regarding the use of the product can be found in the user manual. Before use, read its contents and follow the instructions contained within. Also, read the following information before use:

Usage Warnings

Risk of Damage to the Device:

- Do not expose the device to extreme temperatures, falls, impacts, strong shocks, or other factors that may contribute to its damage.
- Do not expose the device to water unless the manufacturer states that it is waterproof.
- When installing LED strips, ensure that the mounting surface is clean, dry, and free of dust to prevent them from falling and being damaged.
- Do not use fixtures with damaged components, such as broken bulbs, cut LED strips, or damaged mounting brackets.
- Ensure that the devices are properly mounted to prevent accidental falls and damage.

Risk to Children:

- The device is not intended for play and is not suitable for children.
- Smart lights, bulbs, and other lighting components may contain small parts that pose a choking hazard.
- Keep the device and accessories out of reach of children to prevent accidental swallowing of small parts or damage to the product due to improper use.

Risk of Electric Shock:

- Perform installation of the device only when the power is disconnected.
- Use only original power cables, adapters, and connectors supplied by the manufacturer or recommended in the user manual. Do not use the device with damaged cables, plugs, or connectors to avoid short circuits or electric shock.
- If the device is not waterproof, do not install it in areas exposed to moisture, such as bathrooms or outdoor spaces.
- Do not handle connectors or cables with wet hands.

Risk of Overheating and Burns:

- Avoid touching bulbs and fixtures during operation or immediately after turning them off, as they may be very hot.
- Ensure that lamps and bulbs are installed in areas with adequate ventilation to prevent

overheating.

- Do not cover lamps or bulbs with materials that may restrict airflow or cause ignition.

Wireless Connection

Data Protection:

- Smart lighting devices often use Wi-Fi, Bluetooth, or Zigbee. If possible, secure them with a strong password and enable encrypted connections.
- Regularly update the device software and control applications to ensure data security and protection against unauthorized access.

Access Management:

- Limit access to lighting control applications to trusted users only.
- Regularly check the list of devices connected to the network and remove those that are no longer needed or may pose a risk.
- If possible, use the alert function for unauthorized access attempts to devices.

Information on Proper Use

Installation and Configuration:

- Before installation, ensure that all components are properly sized for the chosen installation location.
- Always ensure that devices are securely mounted and connected according to the manufacturer's instructions.
- In the case of outdoor lighting installation, ensure that the device has the correct IP rating and is protected from weather conditions.

Maintenance and Cleaning:

- Regularly check the condition of lighting devices to ensure they are functioning correctly and are not damaged.
- Clean the device with a soft dry cloth. Do not use water or chemical agents that may damage their surface.

Safety of Use: If necessary, check that the device is in good condition:

- Do not leave lighting on unattended, especially with devices that may heat up.
- If you notice sparking, a burning smell, or other signs of malfunction, immediately disconnect the appliance from the power supply and contact the service center.

Additional Safety Measures

Service and Repairs:

- In case of any issues with the appliance, contact an authorized service center.
- Do not attempt to repair the device yourself to avoid further damage or loss of warranty.

Safe Disposal:

- Dispose of used lighting devices in accordance with local electronic waste regulations.
- Do not throw the device in the municipal waste - return it to a local electronics collection point. If you need further information regarding the product, contact customer service (email: hurt@innpro.pl, website: <https://innpro.pl/>) or another expert.

EU DECLARATION OF CONFORMITY

Qingdao Yeemi Innovation Information Technology Co., Ltd. hereby declares that the type of radio equipment Smart Ceiling Light with Edge Lighting Yeelight Mars C300 is in compliance with Directive 2014/53/EU.

The full text of the EU Declaration of Conformity is available at the following internet address: <https://files.innpro.pl/yeelight>

Manufacturer's address: Keyuanwei One Road Building B 266100 Qingdao, cn

Radio frequency: 2480Mhz - 2483.5Mhz

Maximum radio frequency power: <20dBm

Environmental Protection

Electronic waste marked in accordance with the European Union directive must not be disposed of together with other municipal waste. It is subject to separate collection and recycling at designated locations. By ensuring its proper disposal, you will prevent possible negative consequences for the environment and human health. The system for collecting used equipment complies with local environmental protection regulations for waste disposal. Detailed information on this topic can be obtained from the municipal office, processing plant, or the store where the product was purchased. The product meets the requirements of the so-called new approach directives of the European Union (EU), which address issues of safety in use, health protection, and environmental protection, and specify hazards that should be identified and eliminated.

Importer:

INNPRO Robert Błędowski sp. z o.o. Rudzka 65c

44-200 Rybnik, Poland

tel. +48 533 234 303

hurt@innpro.pl

www.innpro.pl

Manufacturer:

Qingdao Yeemi Innovation Information Technology Co., Ltd. Keyuanwei One Road Building B
266100 Qingdao, China

support@yeelight.com

Representative in the EU:

INNPRO Robert Błędowski sp. z o.o. Rudzka 65C

44-200 Rybnik, Poland

zgloszenia@innpro.pl

Warranty

The warranty will be void in the event of changes and/or modifications to the product. The manufacturer is not responsible for any damages resulting from improper use of this product. Disposal

- Dispose of this product at the appropriate collection point.
- Do not throw this product away with municipal waste.
- For more information, contact the retailer or local authorities responsible for waste management.

Documentation

This product has been manufactured and is supplied in accordance with all applicable regulations and directives in force in all member states of the European Union. It also meets all relevant specifications and regulations in the country of sale. Official documentation can be obtained upon request. Official documentation also includes (but is not limited to) the Declaration of Conformity, Safety Data Sheets, and the product testing report.

Disclaimer

The design and specifications of the product may be changed without prior notice. All logos and trade names are registered trademarks of their respective owners and are protected by law.