

ΣΕΤ ασύρματου μικροφώνου γραβάτας Fifine M8, 2 τεμάχια (μαύρο)

Fifine · EAN 5031192994599

Machine translation from Polski. In case of doubt the manufacturer's original document prevails.

M8 USER MANUAL

Graphics: two microphones with receiver

TABLE OF CONTENTS

QUICK START

RANGE OF OPERATION

MONITORING

RESTORING FACTORY SETTINGS

CHARGING

SPECIFICATION

OPERATION NOTES

WHAT'S IN THE BOX? Microphone x2

Receiver x1

USB-C Cable (30 cm) x1

User Manual x1

MICROPHONE

Windshield

Indicator Light

Mute (red light)

Low Battery (red flashing light)

Fully Charged (green light)

Pairing (blue light)

Unpairing (blue flashing light)

Power Button

Press: mute/unmute

Press and hold for 3 seconds:

turn on/off

Clip: adjustable up to 360°

Type-C Port: charging/monitoring

RECEIVER

Indicator Light

Paired (green light)

Unpaired (blue flashing light)

Type-C Connector

Type-C Port: charging/monitoring

Pairing Button (in the hole)

QUICK START

For Android phones/tablets

1. Press and hold the power button on the microphone for 3 seconds until the indicator light starts flashing blue. Graphics: finger pressing the power button on the microphone
2. Connect the receiver to the Type-C port on the phone/tablet. Graphics: connecting the receiver to an electronic device
3. The microphone will connect to the receiver within 5 seconds. (Once connected, the light will remain on). If this does not happen, you need to manually reset the microphone set (see pages 10-11). Graphics: microphone clipped to clothing, receiver connected to smartphone
4. After connecting the microphone, open the camera/recording app on the phone/tablet to test the microphone. You can use the following methods to listen to the recording. (1) Disconnect the receiver and listen to the recording from the built-in speaker of the phone/tablet. Graphics: receiver being disconnected from smartphone
(2) Connect headphones to the Type-C port on the microphone/receiver. Graphics: headphones connected to the receiver

or

Graphics: headphones connected to the microphone

- (3) Use Bluetooth headphones. Tip: If the receiver light is off, check if you need to enable OTG in the phone settings to power the receiver. If the connection is weak due to the phone case, remove it and ensure that the receiver is fully connected to the phone/tablet. The input volume of the microphone and monitoring cannot be adjusted. For iPhone/iPad

To connect the receiver to an iPhone/iPad, you need the original Apple Lightning (male) to USB (female) adapter and a USB (male) to Type-C (female) adapter. (Adapters are not included in the package). Graphics: Apple Lightning to USB adapter

RANGE OF OPERATION

Indoors: 65 feet (maximum)

Outdoors: 50 feet (maximum)

Tips:

Range may be affected by obstacles such as large metal objects. If you exceed the recommended range, the indicator on the microphone and receiver may flash blue due to loss of connection.

MONITORING

Connect headphones (Type-C connector) to the microphone or receiver for real-time monitoring. You will hear both the sound from the device and the microphone. When the headphones are connected to the microphone (not to the receiver), you will hear the following voice prompts during operation. (1) Power On (when the microphone is turned on) (2) Power Off (when the microphone is turned off) (3) Connection (when the microphone connects to the receiver) (4) No Connection (when the microphone does not connect to the receiver) (5) Microphone Off (when you mute the microphone) (6) Microphone On (when you unmute the microphone)

Tip:

If the headphones have a 3.5 mm connector, you will need a Type-C (male) to 3.5 mm (female) digital-analog adapter. (This adapter is not included in the package). Graphics: digital-analog adapter

If the headphones transmit a digital signal, they may not be compatible with this microphone, and sound from the microphone may not be heard.

RESTORING FACTORY SETTINGS

If the indicator continues to flash blue (unpaired), follow the steps below to reset the device.

1. Disconnect the receiver and turn off the microphone.
2. Turn on the microphone and connect the receiver to the phone/tablet. (The indicator on the receiver and microphone will start flashing). Graphics: finger pressing the power button on the microphone

Graphics: receiver being connected to the tablet

3. Using a pin, press the pairing button located in a small hole on the receiver. Graphics: hand pressing the pairing button with a pin
4. The blue light on the receiver will stop flashing for about 1 second. At this moment, you need to quickly press the power button on the microphone twice. Press twice
5. After a few seconds, the flashing light on the receiver and microphone will remain on, and the receiver will be successfully paired with the microphone.

CHARGING

1. The microphone has a built-in battery.

After a full charge, the indicator lights up green. After 2 hours of charging, the battery lasts for 5-6 hours of operation. 2. The receiver does not have a built-in battery. It is powered by the phone/tablet. You can also use the Type-C port to charge the phone while using the microphone to avoid battery drain. (Note: iPhone/iPad and some Android phones do not support this feature). Tip: After disconnecting the receiver from the device for 5 minutes, the microphone will automatically turn off to save energy. SPECIFICATION

Frequency: 2.4 GHz ~ 2.483 GHz

Directional characteristic: omnidirectional

Power supply: 5 V

Sensitivity: -32 dBV (1 kHz 94 dBSL)

Sampling frequency conversion: 16 bits/48 kHz

Max. SPL: 108 dB

Frequency response: 50 Hz~15 kHz

USAGE NOTES

When using the device, keep it away from water. The device should be kept away from fire. Since it is a wireless device, keep it away from other sources of interference. Do not disassemble the microphone set into parts. Use a standard power supply, as high voltage may damage the device. The used microphone set should be disposed of properly. It should be placed in the trash and not thrown on the ground. CONTACT US

Social media:

Contact information:

More product information can be found on the website. Company website:

<https://fifinemicrophone.com/>

WARRANTY

FiFine provides a warranty for material and workmanship defects in its microphone products for a period of one year from the date of original retail purchase, provided that the purchase was made from an authorized FiFine microphone dealer. This warranty is void in the event of modification, misuse, improper handling, excessive wear, or servicing of the equipment by unauthorized parties. To avail of warranty service, please contact your local distributor or web@fifine.cc. SIMPLIFIED EU DECLARATION OF CONFORMITY

FIFINE hereby declares that the type of radio device Wireless Lavalier Microphone Set Fifine M8 is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following website: <https://files.innpro.pl/Fifine>

Manufacturer's address:

Zhaoqing Junfeng Electronics Co., Ltd. Waijing Industry Village, No. 6, Duanzhou 3rd Road,

Zhaoqing

518016 Guangdong Province, China

sales36@fifinedesign.com

Radio frequency: 2.4GHz

Maximum radio frequency power: 2400-2483.5 MHz

Representative in the EU:

Unico authentication technology service SARL

Chez Domideal 11 Avenue Carnot 11

25000 BESANCON, Doubs, France

info@unic-sarl.cn

Environmental protection

Used electronic equipment marked in accordance with the European Union directive must not be placed together with other municipal waste. It is subject to selective collection and recycling at designated points. By ensuring its proper disposal, you prevent potential negative consequences for the natural environment and human health. The system for collecting used equipment complies with locally applicable environmental regulations regarding waste disposal. Detailed information on this can be obtained from the municipal office, waste management facility, or the store where the product was purchased. The product meets the requirements of the so-called New Approach directives of the European Union (EU) concerning safety, health protection, and environmental protection, identifying hazards that should be detected and eliminated. This document is a translation of the original user manual created by the manufacturer. Detailed information about the distributor/manufacturer warranty conditions is available on the website

<https://serwis.innpro.pl/gwarancja>

The product should be regularly maintained (cleaned) by the user or by specialized service points at the user's cost and responsibility. In the absence of information about necessary periodic or service maintenance actions in the user manual, the user should regularly, at least once a week, assess the physical condition of the product against that of a physically new product. If any deviation is detected or identified, urgent maintenance (cleaning) or servicing steps should be taken. Failure to perform proper maintenance (cleaning) and respond upon detection of a deviation may lead to permanent damage to the product. The warranty does not cover damages resulting from neglect. Importer:

INNPRO Robert Błędowski sp. z o.o. ul. Rudzka 65c

44-200 Rybnik, Poland

tel.

+48 533 234 303

hurt@innpro.pl

www.innpro.pl

Safety Instructions

Before starting to charge, check if the device contacts are clean. Never leave the device unattended while in use and charging. Ensure that you can quickly disconnect the device from the power source in case of an emergency. Never expose the device to high temperatures. Charge the device in a dry and well-ventilated area away from flammable materials, maintaining a minimum distance of 1m from other objects. Never cover the device while charging. Never use a power supply, charging station, cables, etc., without the manufacturer's recommendation and certification. Take care of your property; the device is equipped with cells that are difficult to extinguish, so equip yourself with a fire blanket. LI-ION Battery

The device is equipped with a LI-ION (lithium-ion) battery, which, due to its physical and chemical structure, ages over time and with use. The manufacturer specifies the maximum operating time of the device under laboratory conditions, where optimal working conditions for the device exist, and the battery itself is new and fully charged. Actual operating time may differ from the declared time in the offer and this is not a defect of the device but a feature of the product. To maintain maximum battery life, it is not recommended to discharge it below 3.18V or 15% of total capacity. Lower values, such as 2.5V for the cell, permanently damage it and this is not covered by warranty. If the battery or the entire device is not used for more than one month, the battery should be charged to 50% and its charge level should be checked periodically every two months. Store the battery and device in a dry place, away from sunlight and negative temperatures. LI-PO Battery

The device is equipped with a LI-PO (lithium-polymer) battery, which, due to its physical and chemical structure, ages over time and with use. The manufacturer specifies the maximum operating time of the device under laboratory conditions, where optimal working conditions for the device exist, and the battery itself is new and fully charged. Actual operating time may differ from the declared time in the offer and this is not a defect of the device but a feature of the product. To maintain maximum battery life, it is not recommended to discharge it below 3.5V or 5% of total capacity. Lower values, such as 3.2V for the cell, permanently damage it and this is not covered by warranty. If the battery or the entire device is not used for more than one month, the battery should be charged to 50% and its charge level should be checked periodically every two months. Store the battery and device in a dry place, away from sunlight and negative temperatures. Product Battery Specifications

Feature Value

Battery Category Portable Battery

Battery Type Portable lithium-polymer batteries (Li-Po)

Contains Cadmium/Lead (>0.002% Cd, No
>0.004% Pb)

Net Weight (kg) 0.003

Capacity (mAh) 150