

magnetic selfie monitor screen



User Guide

Disclaimer


Please read this statement carefully and by using this product you will be deemed to have acknowledged and accepted it in full. Please check the product carefully before each use and do not use it if damaged or deformed. By using this product, you acknowledge and agree that you are fully responsible for your actions and the possible consequences of using this product. You undertake to use this product only for legitimate and lawful purposes. You understand and agree that ("Telesin") shall not be liable for any misuse, adverse effects, damages, injuries, penalties or other legal consequences arising directly or indirectly from the use of this product. The user should follow the precautions including but not limited to those mentioned herein. To the extent Telesin reserves the right to interpret and modify this commitment within the limits of national laws and regulations.

The warranty period for TELESIN products begins 6 months on the day you receive the product.

Product Introduction

This product is a wireless screen casting device that allows users to mirror their smartphone display onto its 4-inch screen. Equipped with Bluetooth remote control functionality, it enables photo/video capture via physical buttons and zoom knobs. Ideal for selfies, live streaming, and short video creation.

Product Diagram



- 1 Power Button
- 2 Status Indicator
- 3 Capture Button
- 4 Display Screen
- 5 Brightness Key
- 6 Mode Key
- 7 Zoom Knob
- 8 Lanyard Hole
- 9 Type-C Charging Port
- 10 MagSafe Magnet


Connection Steps

1. Power On


Press and hold the Power button for 2 seconds to turn on the device power (the system startup requires 6 seconds).

2. Connect Mobile Phone via Bluetooth

- Turn on the Bluetooth function on your phone and search for devices to pair.
- In the list of device names, search for: **TELESIN_RC3-XXXXXX** (the last six digits are generated by the system). Tap to pair. Once paired successfully, you can use the Bluetooth control functions.



- For Apple Phones: If only the camera shutter button works after Bluetooth connection and other button functions are unavailable, perform the following steps:
 - Go to Settings → Accessibility → Zoom.
 - Set the Zoom Region to Full Screen Zoom.




* (When the "Zoom" button is turned on, the phone screen will magnify. Double-tap the screen with three fingers to restore normal size).

3. Screen Mirroring (iOS System)


- Open the Wireless LAN on your phone, search for the screen mirroring device's SSID, and enter the password to connect wirelessly.

- Name: **TELESIN_RC3_XXXXXX**
- Password: **123456**



- Open the Screen Mirroring function on your phone. The screen mirroring device's SSID will pop up. Tap to connect and start screen mirroring.

Note: If no screen mirroring connection is made within 5 minutes, the device will automatically power off due to timeout.




4. Screen Mirroring (Android System & HarmonyOS)

- Swipe down on the phone screen to find the "Wireless Cast"/"Wireless Projection" function, tap the device SSID to start wireless screen mirroring after it is found.


Alternatively: Open phone Settings → Search for "Wireless Cast"/"Wireless Projection" → Turn on "Wireless Cast"/"Wireless Projection".

- Note: If no screen mirroring connection is made within 5 minutes, the device will automatically power off due to timeout.




5. Switch Language (Chinese/English) on Startup Screen

- After the startup animation ends, wireless connection instructions will appear.
- Double-click the Brightness button to switch between Chinese and English instructions.



Functions



Camera Control Mode

No.	Operation	Function
1 Power Key	Long press 2 sec	Power ON (displays connection screen) / Power OFF
	Single click	When connected to Bluetooth and the phone camera is open: Flip front/rear camera
2 Shutter Key	Single click	When connected to Bluetooth and the phone camera is open: Start taking photo or recording video
	Long press 2 sec	When connected to Bluetooth: Quickly open phone camera from sleep/locked screen
3 Brightness Key	Single click	Brightness adjustment (one step per click, three levels total)
	Single click	Flips the display content 180 degrees vertically.
4 Mode Key	Long press 2 sec	Toggles between mirrored and non-mirrored display.
	Rotate Up	When connected to Bluetooth and the phone camera is open: Camera zoom in
5 Knob	Rotate Down	When connected to Bluetooth and the phone camera is open: Camera zoom out
	Long press 3 sec simultaneously	Restore factory settings (Remove paired devices)

Charging Function

No.	Operation	Function
1 Battery Level Indicator (s)	Insert Type-C charging cable	Green light breathing during charge; Solid green when fully charged
	Low Battery	Red light flashing
2 Status Indicator (s)	Taking photo / Liking video	Indicator flashes once


Wireless Connection

Connection Type	Status	Function
Blue-tooth	Pairing	Green light flashes continuously
	Paired	Green light solid for 3 seconds; Bluetooth icon shows connection status.
Casting	Successful	Casting icon shows connection status.
	Timeout	Device automatically powers off if no casting connection is made within 5 minutes.
	Out-of-Range	Auto-reconnect supported when back in range. Press any key to wake up device and initiate reconnection.

Specifications

Product Dimensions	109mm × 59mm × 13.9mm
Product Weight	105g
Material	Plastic + Hardware
Screen Size	4 inches
Screen Resolution	540 × 1080P
Battery life	>3 hours
Power Input	5V ■ 2A
Battery Capacity	1800mAh/3.7V
Power Input Port	USB-C
Wireless Transmission	WiFi + Bluetooth
Operating Temperature	0~40°C
Charging Temperature	0~45°C

Package Contents



- 1 Main Unit ×1
- 2 Magnetic Ring ×1
- 3 Charging Cable ×1
- 4 Wrist Strap ×1
- 5 User Manual ×1

Safety Tips

- This product is a precision instrument. Please avoid dropping, colliding or heavy impact during use.
- Do not place the product in areas with corrosive chemicals to prevent corrosion, which may cause the product to malfunction.
- Please clean the product with a soft, dry cloth.
- Do not place the product in excessively high temperatures, as this may damage or cause the internal battery to explode.
- Do not disassemble or repair the machine by yourself
- This manual has been prepared based on rigorous testing by our company. Design and specifications are subject to change without prior notice.

FCC Caution

15.19 Labelling requirements.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

15.21 Information to user.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

15.105 Information to the user.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-Reorient or relocate the receiving antenna.
-Increase the separation between the equipment and receiver.
-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

IC Statement

-English:

This device contains licence-exempt transmitter (s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS (s). Operation is subject to the following two conditions:
(1) This device may not cause interference.
(2) This device must accept any interference, including interference that may cause undesired operation of the device.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
RF exposure statement:
The device was evaluated to meet general RF exposure requirements. The device can be used in portable exposure condition without restriction.

- French:

Cet appareil contient des émetteurs / récepteurs exempts de licence conformes aux RSS (RSS) d'Innovation, Sciences et Développement économique Canada. Le fonctionnement est soumis aux deux conditions suivantes:
(1) Cet appareil ne doit pas causer d'interférences.
(2) Cet appareil doit accepter toutes les interférences, y compris celles susceptibles de provoquer un fonctionnement indésirable de l'appareil.

Tout changement ou modification non expressément approuvé par la partie responsable de la conformité pourrait annuler l'autorité de l'utilisateur à utiliser l'équipement.

Déclaration d'exposition RF:

L'appareil a été évalué pour répondre aux exigences générales en matière d'exposition aux RF. L'appareil peut être utilisé en condition d'exposition portable sans restriction.

Declaration of Conformity

