

Inteligentna lampa sufitowa RGB Yeelight Yeelight Jupiter D C400

YEELIGHT · EAN 6924922261322

Machine translation from Čeština. In case of doubt the manufacturer's original document prevails.

Yeelight RGB Smart Ceiling

Light Jupiter D

User Manual

Product Introduction

Front view of the lamp cover Back view of the lamp cover

Mounting hole for

self-tapping

screw

Wire hole

Mount the base plate

ON

OFF

Expansion plug-

screw Remote

controller

Installation Instructions

1. Before installation, ensure that the main power is turned off:

2. Remove the product from the packaging and by turning the lamp cover to the left, find the mounting base:

ON

ON

ON ON

ON

ON

OFF

OFF OFF TO

3. Place the base on the prepared spot on the ceiling and use a pencil to mark the drilling

points, remove the base and drill holes with a diameter of 6 mm at the marked points:

4. Insert the plugs into the drilled holes of 6 mm diameter, then attach the mounting base to the mounting points and secure the lamp to the ceiling using self-tapping screws:

5. Pull the wires from the ceiling and gradually connect the phase wire (brown), protective wire (yellow-green), and neutral wire (blue) to the lamp's junction box at the points marked with the letters L, N, screw them clockwise and push the excess wires back into the ceiling:

6. Check that the lamp cover is not damaged or deformed, if everything is fine, align the cover with the latch on the base and screw it clockwise until it is securely fastened. Avoid excessive force to prevent damaging the lamp cover:

7. After completing the installation, recheck the fastening of the base and lamp cover and clean the surface of the lamp:

8. After finishing the lamp installation, ensure that you turn the power back on after people leave the area:

9. After turning on the lamp, set it according to the instructions in the app:

ON ON

ON

ON

ON

OFF OFF OFF

Parameter Information

Smart Smart Smart

Lighting Lighting Lighting

Product Name

Ceiling Jupiter

Ceiling Jupiter

D C400

Ceiling Jupiter

40W

Rated Power

Rated

Voltage

2500 lm

Luminous Flux

Color Temperature

Dimension

Wireless Connection: Wi-Fi IEEE 802.11 b/g/n, 2.4 GHz, Bluetooth 4.2 BLE

Supported Platforms: Android 8.40 and iOS 12.0 or newer

Transmitter Power (dBm): 20 dBm

Connect to the Mi Home App

Download the App

Search for "Mi Home" in the app store or scan the QR code to download and install the app.

Add Device

- Go to the main page of the Mi Home app, click the "+" icon in the upper right corner, and add your device.
- Follow the instructions displayed in the app to configure the device.
- After successfully adding the device, you will find it in the device list.

About the "Connected to Mi Home" Feature

About the "Connected to Mi Home" feature:

"Connected to Mi Home" means that the product can be controlled using the Mi Home app or Xiao AI. It should be noted that "Connected to Mi Home" relates solely to software-level verification. Xiaomi and Mi Home do not assume responsibility for manufacturing, compliance with standards, quality control, or other aspects related to this product and its manufacturer.

Xiaomi HyperOS

Connect

works with

Scan the code to

download the Mi Home app

Warning: Due to app updates, operational steps may differ from those described here. Follow the instructions displayed in the app. This product can also be controlled using Google Home or Amazon Alexa apps. Download and install one of these apps from the app store and then follow the instructions in the app to set up the device. After configuration is complete, you can control the lighting using the app.

Factory Reset

To restore the factory settings of the ceiling light, turn it on and off five times in a row using the wall switch (turn off the light, wait two seconds, turn on the light, wait two seconds – this counts as one turn on). After the fifth turn on, the light will start to pulse. After five seconds, it will automatically restart and the factory settings of the light will be restored.

Warning: When using the ceiling light in a new network environment, it is necessary to

restore the factory settings and reconnect to the network.

How to connect and use the remote control

Ensure that the remote control and ceiling light are in the same room. Turn on the light and within 60 seconds do the following: simultaneously press the "OFF" and "M" buttons on the remote control and immediately release them. The indicator on the remote control will start to blink, indicating that pairing is in progress. If the indicator blinks cyclically, pairing was successful.

ON Turn on the light Set color temperature

OFF Turn off the light M

Switch modes

+ Increase brightness

Decrease brightness

Precautions

1. The fixture must be installed by a professional or qualified electrician.
2. Keep accessories and packaging bags out of reach of children, they are not toys.
3. Disconnect all power circuits during installation.
4. This fixture contains a light source with energy class D.
5. The light source must be replaced by a specialist.
6. The separate power control device must be replaced by a specialist. This document is a translation of the original user manual created by the manufacturer. Detailed information about the warranty conditions of the distributor/manufacturer is available on the website <https://serwis.innpro.pl/gwarancja>

The product must be regularly maintained (cleaned) by the user or a specialized service center at the user's expense. If the user manual does not provide information on necessary periodic maintenance or service operations, the physical condition of the product must be assessed regularly, at least once a week, to determine any deviation from that of a physically new product. If any deviation is detected or found, maintenance (cleaning) or service measures must be carried out immediately. If proper maintenance (cleaning) is not performed and no action is taken regarding the identified different condition, permanent damage to the product may occur. The guarantor is not liable for damages resulting from negligence.

Warnings and safety information

All information regarding the use of the product can be found in the user manual. Read its contents before use and follow the instructions contained therein. Also read the following

information before use:

Usage warnings

Risk of damage to the device:

- Do not expose the device to extreme temperatures, falls, impacts, strong shocks, or other factors that may contribute to its damage.
- Do not expose the device to water unless the manufacturer states that it is waterproof.
- When installing LED strips, ensure that the mounting surface is clean, dry, and dust-free to prevent them from falling and being damaged.
- Do not use fixtures with damaged components, such as broken bulbs, cut LED strips, or damaged mounting brackets.
- Ensure that the devices are properly mounted to prevent accidental falls and damage.

Risk to children:

- The device is not intended for play and is not suitable for children.
- Smart lights, bulbs, and other lighting components may contain small parts that pose a choking hazard.
- Keep the device and accessories out of reach of children to prevent accidental swallowing of small parts or damage to the product due to improper use.

Risk of electric shock:

- Perform the installation of the device only when the power is disconnected.
- Use only original power cables, adapters, and connectors supplied by the manufacturer or recommended in the user manual. Do not use the device with damaged cables, plugs, or connectors to avoid short circuits or electric shock.
- If the device is not waterproof, do not install it in areas exposed to moisture, such as bathrooms or outdoor spaces.
- Do not handle connectors or cables with wet hands.

Risk of overheating and burns:

- Avoid touching bulbs and fixtures while in operation or immediately after turning them off, as they may be very hot.
- Ensure that lamps and bulbs are installed in areas with adequate ventilation to prevent overheating.
- Do not cover lamps or bulbs with materials that may restrict airflow or cause ignition.

Wireless connection

Data protection:

- Smart lighting devices often use Wi-Fi, Bluetooth, or Zigbee. If possible, secure them with a strong password and enable encrypted connections.

- Regularly update the device software and control applications to ensure data security and protection against unauthorized access.

Access management:

- Limit access to lighting control applications to trusted users only.
- Regularly check the list of devices connected to the network and remove those that are no longer needed or may pose a risk.
- If possible, use the alert feature for unauthorized access attempts to devices.

Information on proper use

Installation and configuration:

- Before installation, ensure that all components are properly sized for the chosen installation location.
- Always ensure that devices are securely mounted and connected according to the manufacturer's instructions.
- In the case of outdoor lighting installation, ensure that the device has the correct IP rating and is protected from weather conditions.

Maintenance and cleaning:

- Regularly check the condition of lighting devices to ensure they are functioning properly and are not damaged.
- Clean the device with a soft dry cloth. Do not use water or chemical agents that could damage their surface.

Safety of use: If necessary, a check should be performed to ensure that the device is in good condition:

- Do not leave lighting on unattended, especially with devices that may heat up.
- If you notice sparking, a burning smell, or other signs of malfunction, immediately disconnect the appliance from the power supply and contact the service center. Additional safety measures

Service and repairs:

- In case of any problems with the appliance, contact an authorized service center. • Do not attempt to repair the device yourself to avoid further damage or loss of warranty. Safe disposal:

- Dispose of used lighting equipment in accordance with local electronic waste regulations. • Do not throw the device in the municipal waste - return it to the local electronics collection point. If you need further information regarding the product, contact customer service (email: hurt@innpro.pl, website: <https://innpro.pl/>) or another expert. EU DECLARATION OF

CONFORMITY

Qingdao Yeemi Innovation Information Technology Co., Ltd. hereby declares that the type of radio equipment Intelligent lamp sufitowa RGB Yeelight Yeelight Jupiter D C600 is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at: <https://files.innpro.pl/yeelight>

Manufacturer's address: Keyuanwei One Road Building B 266100 Qingdao, cn

Radio frequency: 2480Mhz - 2483.5Mhz

Maximum radio frequency power: <20dBm

Environmental protection

Electronic waste marked in accordance with European Union directives must not be disposed of together with other municipal waste. It is subject to separate collection and recycling at designated locations. By ensuring its proper disposal, you prevent possible negative consequences for the environment and human health. The collection system for used equipment complies with local environmental protection regulations for waste disposal.

Detailed information on this topic can be obtained from the municipal office, processing plant, or store where the product was purchased. The product meets the requirements of the so-called new approach directives of the European Union (EU), which address issues of safe usage, health protection, and environmental protection and specify hazards that should be identified and eliminated. Importer:

INNPRO Robert Błędowski sp. z o.o. Rudzka 65c

44-200 Rybnik, Poland

tel. +48 533 234 303

hurt@innpro.pl

www.innpro.pl

Manufacturer:

Qingdao Yeemi Innovation Information Technology Co., Ltd. Keyuanwei One Road Building B 266100 Qingdao, China

support@yeelight.com

Representative in the EU:

INNPRO Robert Błędowski sp. z o.o. Rudzka 65C

44-200 Rybnik, Poland

zgloszenia@innpro.pl

Warranty

The warranty will be voided in case of changes and/or modifications to the product. The manufacturer is not responsible for damages resulting from improper use of this product.

Disposal

- Dispose of this product at the appropriate collection point.
- Do not throw this product in municipal waste.
- For more information, contact the retailer or local authorities responsible for waste management.

Documentation
This product has been manufactured and is supplied in accordance with all relevant regulations and directives applicable in all member states of the European Union. It also meets all relevant specifications and regulations in the country of sale. Official documentation can be obtained upon request. Official documentation also includes (but is not limited to) the Declaration of Conformity, Safety Data Sheets, and product testing reports.

Disclaimer
The design and specifications of the product may be changed without prior notice. All logos and trade names are registered trademarks of their respective owners and are protected by law.