

EJEAS Ενδοεπικοινωνία για Κράνος Μηχανής Q2 (Μαύρο)

EJEAS · EAN 5906168433955

Machine translation from Polski. In case of doubt the manufacturer's original document prevails.

User Manual

Motorcycle

Intercom System

Product Details

Indicator Antenna

Power / Phone Button

Intercom /

FM Button

Volume +

Volume - Type - C Headset Interface

Product Installation

Product Operations

Operation Diagram

Double click

Single click

Long press for 5s Simultaneous click

Basic Operations

On / Off Please charge before use. Off

On

Tone Signal

Press < Phone Button > and

< Intercom Button > simultaneously. Blue light

→

Lights off

blinks slowly

Battery Level

" Battery Level High "

or

? " Battery Level Medium "

" Battery Level Low "

Low Battery Indicator Charging Indicator

Red light blinks twice Charging

Solid red Czer-

? " Low Battery Level "

Full light goes out

FM and intercom volume can be used simultaneously. Intercom / Calling / Music / FM

When intercom and FM are used simultaneously, FM volume control

Factory Reset

Press and hold < Volume + >, < Volume - >, < Phone Button > simultaneously for 5s. Red and blue lights blink quickly

four times simultaneously

? " Restore Default Settings "

Bluetooth Intercom

Intercom Pairing

1 Press and hold < Intercom Button >

for 5s to enter pairing mode. Red and blue lights

blink quickly alternately

? " Intercom Pairing "

Searching and pairing. Pairing successful. ? " Intercom Pairing

Successful "

Connected, start communication. Reconnecting Intercom Disconnecting Intercom

? " Intercom Connected " ? " Intercom Disconnected "

Compatible with Old Intercom Pairing

(1) Press and hold < Volume - >

and < Intercom Button > simultaneously for

5s, while V4 / V6 enters pairing mode. Red and blue lights blink quickly

alternately

or

2) Click < Intercom Button >

to enter Bluetooth search mode. Red and blue lights blink twice

alternately

? " Searching for Intercom "

Pairing successful. Blue light blinks slowly

3 Click < Intercom Button > to

connect. Pairing Other Bluetooth Devices

This function does not guarantee compatibility with all Bluetooth headsets or

Bluetooth intercoms available on the market. 1 Press and hold < Intercom Button >

for 5s to enter pairing mode. Red and blue lights

blink quickly alternately

? " Intercom Pairing "

2) Click < Intercom Button >

to enter Bluetooth search mode. Red and blue lights

blink twice

alternately

? " Searching for Intercom "

3 Other devices enter

Supports Bluetooth search mode. other

protocol

HFP

Pairing successful. ? " Intercom Pairing Successful "

Bluetooth Pairing

Phone Pairing

1 Press and hold < Phone Button >

for 5s to enter pairing mode. (If no phone is connected, it will exit

pairing mode after 2 minutes)

Red and blue lights blink

quickly alternately

? " Phone Pairing "

2 Open Bluetooth on your phone,

search and pair with

the device. Pairing successful. Blue light blinks slowly twice

" Pairing successful, Connected "

The current battery status will be displayed on your phone. (Phone must support HFP)

Reconnecting to phone

Automatic connection

or

return to the last paired. Mobile phone

Answering a call

Automatic answering within 8s. or

if no operation is performed. Redial last number Ending the call

Rejecting a call

TEL priority while listening to music / FM / intercom, and answering a phone call. music

intercom music intercom

Connection Interrupt Disconnect Restore

Voice Assistant

Phone must support and have voice assistant enabled (Google Assistant & Siri). Voice

Assistant

Activate voice assistant. Press and hold < Phone > button for 1s. Music Control Play-

/Pause Music Switch Music

FM Radio

Turn FM On / Off

Automatic search and radio, intercom and radio can operate simultaneously. Double click <

FM Button > to turn on FM. Blue light stays on for 4s

Red light blinks quickly twice ? " Ra-

dio FM "

Double click < FM Button > to turn off FM.

" FM Radio Off "

Frequency Switching

Frequency - Frequency +

EUC Remote Control (optional)

EUC Details

Unnecessary Button

Unnecessary Button

Intercom Button

Volume +

Phone

Volume -

EUC Pairing

1 Long press both < FM Button > and

< Volume - > EUC for 5s to clear

the EUC pairing record. The red and blue lights stay on

2 Long press both < Phone Button > and

< Volume - > for 5s. The red and blue lights flash alternately and quickly

? " Remote Control Pairing "

any button

3 Click any EUC button. Pairing successful? " Pairing Complete "

(If the EUC is not paired within 2 minutes, it will automatically exit pairing mode.)

FM ON/OFF

Click < FM Button > to turn on FM. Click < FM Button > to turn off FM. NOTE: This device has been tested and found to comply with the requirements for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a

In case of discontinuing the use of the battery or the entire device for more than one month, the battery should be charged to 50% and its charge level should be checked periodically every two months. Store the battery and device in a dry place, away from sunlight and negative temperatures. LIPO Battery The device is equipped with a LI PO (lithium-polymer) battery, which due to its physical and chemical structure ages over time and with use. The manufacturer specifies the maximum operating time of the device under laboratory conditions, where optimal working conditions for the device exist, and the battery itself is new and fully charged. The actual operating time may differ from that declared in the offer and this is not a defect of the device but a feature of the product. To maintain maximum battery life, it is not recommended to discharge it below 3.5V or 5% of the total capacity. Lower values, such as 3.2V for the cell, permanently damage it and this is not covered by the warranty. In case of discontinuing the use of the battery or the entire device for more than one month, the battery should be charged to 50% and its charge level should be checked periodically every two months. Store the battery and device in a dry place, away from sunlight and negative temperatures. Product Battery Specifications Feature Value Product Code Q2 EAN Code 5906168433955 Battery Category Portable Battery Battery Type Portable lithium-ion (Li-Ion) batteries Contains Cadmium/Lead (>0.002% Cd, - >0.004% Pb) Net Weight (kg) 0.0014 Capacity (mAh) 750 Power (W) 2.5-5