

Φωτιστικό οροφής Lepro E1-60

LEPRO · EAN 4894495041732

Machine translation from Polski. In case of doubt the manufacturer's original document prevails.

Lepro

Lepro E1-60 Outdoor Lamp

Table of Contents

Contents of the package

01-02

Connection to the app 03-06

Installation 07-09

Notes 10-15

E1-30

X1 X 30

15 lights

X2

E1-60

X1 X 60

15 lights

X4

E1-90

X1 X 90

15 lights

X6

11mm / 0.43in

in

77

1. /

mm

45 22.5mm

0.89in

38mm / 1.50 in 20.5mm / 0.81in 14mm / 0.55in

Model: E1-30 SKU: E1-30-US E1-30-EU E1-30-UK

29V 0.82A, 24W, RGB+(CCT Warm White ~ Cool White), IP65,
15.3 m/50ft (Total), -20°C~40°C (-4°F~104°F)

FCC ID :2A3MAE1 IC: 27538-E1 HVINġ E1-30

L70B50 lifespan: 15,000 hours

Model: E1-60 SKU: E1-60-US E1-60-EU E1-60-UK

29V 1.24A, 36W, RGB+(CCT Warm White ~ Cool White), IP65, 30.6m/100ft (Total), -
20°C~40°C (-4°F~104°F)

FCC ID :2A3MAE1 IC: 27538-E1 HVINġ E1-60

L70B50 lifespan: 15,000 hours

Model: E1-90 SKU: E1-90-US E1-90-EU E1-90-UK

29V 1.65A, 48W, RGB+(CCT Warm White ~ Cool White),
IP65, 45.9m/150ft (Total) -20°C~40°C (-4°F~104°F)

FCC ID :2A3MAE1 IC: 27538-E1 HVINġ E1-90

L70B50 lifespan: 15,000 hours

-1-

0.51m (1.67 ft)

US 100-240V~ 50/60Hz

EU 220-240V~ 50/60Hz

UK 220-240V~ 50/60Hz

Maximum series connections for the same type of product:

E1-30: Up to 3 strings (45 lights)

E1-60: Up to 5 strings (75 lights)

E1-90: Up to 6 strings (90 lights)

Connection to the app

1

Download on the Get it on

App Store Google Play

+

7.0 +

Android iOS 13.0 WiFi 2.4 i GHz

Lepro

2 Bluetooth

Turn on your phone's Bluetooth and connect to the Wi-Fi network. -3-

3

Device Group Rule

The waterproof power connection box is not included in the package. Follow the on-screen steps to complete the configuration. -4-

Voice control

Smart Integration Alexa

A G Alexa SKILL

Alexa Google Assistant

or Alexa App

Lepro Google Google ACTION

Home Me

Google Home App

If the light does not work, go to the Alexa or Google Home app and click DISCOVER DEVICES.

-5-

How to reset the light

ON / OFF

(1) (2)

Press and hold the controller switch button for 5 seconds. -6-

1 Turn on the lights and pair the product with the app to ensure they are working correctly. 2 Clean and dry the surface of the house eave to ensure optimal installation. 3 Install the lights 5-12 cm from the wall surface. a) Use adhesive tape on the back of the lights. b) For secure mounting, especially on rough surfaces, it is recommended to use screws.

1

2

3

<0.51m

<1.67 ft

5~12cm

2.0~4.7in

a

b

M6*24.5mm

KA3*15mm

SKUs*:

E1-30-EU E1-30-UK E1-60-EU E1-60-UK E1-90-EU E1-90-UK

<https://www.lepro.com/docs/>

US: 2412MHz-2462MHz(WiFi)

Operating frequency range 2402MHz-2480MHz(Bluetooth)

2412MHz-2472MHz(WiFi)

EU&UK:

2402MHz-2480MHz(Bluetooth)

Modulation type DSSS(DBPSK/DQPSK/CCK)

OFDM(BPSK/QPSK/16QAM/64QAM)

GFSK

Maximum transmission power 20 dBm e.i.r.p

Antenna type PCB Antenna

(Instructions and safety information) 25

1. Ensure that you connect the adapter to a power supply with the appropriate input voltage and power, as indicated on the adapter. 2. Before using or reusing, carefully inspect the product. Discard any products that have cut, damaged, or frayed wire insulation, cracks in lamp sockets or housings, loose connections, or exposed copper wire. 3. Do not mount or place near gas or electric heaters, fireplaces, candles, or other similar heat sources. 4. Do not install in enclosed spaces. 5. It is normal for the lights to turn on automatically for self-check after each power-on. 6. Do not leave the light on the power cord or any other wire. 7. The controller contains a signal receiver. Avoid placing the controller in a metal, shielded box. It can be stored outdoors, but do not soak it in water. 8. Remember to place the power plug in a waterproof electrical box. 9. Do not hang decorations or other items on the wire, cord, or light string. 10.

Do not close the doors or windows of the product or extensions, as this may cause damage to the insulation of the wires. 11. Do not cover the product with fabric, paper, or any material that is not part of the product during use. 12. Do not modify or replace the plug. 13. The lamps are not suitable for covering with thermal insulation material. 14. The light source of this fixture is not replaceable; when the light source is exhausted, the entire fixture must be replaced. 15. In case of breakage or damage to the lamp, do not use the cord or turn on the power, but safely dispose of it. 16. LED module: luminous flux < 40 lumens, based on test data for a length of 1 meter. It does not belong to light sources. 17. This lamp is intended for decorative purposes. 18. Decorative mood lamp – not suitable for lighting domestic rooms. 19. Do not connect the cord to the power supply while it is still in the packaging. 20. The light chain cannot be trimmed to the appropriate length. 21. This light source is intended solely for applications requiring high-quality colored light. Using this light source will lead to higher energy costs compared to a more energy-efficient equivalent of the product. 22. Light

sources with adjustable color purity minimum excitation:

Blue 440nm – 490nm 90%

Green 520nm – 570nm 65%

Red 610nm – 670nm 95%

23. Only supports dimming via the app. 24. This product is subject to the provisions of the European Directive 2012/19/EU. The symbol representing a crossed-out waste bin indicates that the product requires selective waste collection in the European Union. This applies to both the product itself and all accessories marked with this symbol. Products marked with this symbol must not be disposed of with normal household waste but should be delivered to a collection point for recycling electrical and electronic equipment. This recycling symbol indicates, for example, an item or parts of material as valuable for recycling. Recycling helps reduce the consumption of raw materials and protect the environment. LEPRO INNOVATION INC

3651 Lindell Road Suite D1048, Las Vegas, NV 89103, USA

www.lepro.com 1 866-287-2558 cs@lepro.com

Le Ming Trading Inc. 801-6081 No. 3 Rd. Richmond, BC, V6Y 2B2, CA

www.lepro.ca 1 833-433-1453

cs@lepro.ca

Manufacturer:

One Spencer Dock, North Wall Quay, Dublin 1, D01 X9R7, Ireland

www.lepro.de 49 800-723-6202 cs@lepro.de

www.lepro.co.uk

Made in China

EU representative information: LE Innovation Limited

One Spencer Dock, North Wall Quay, Dublin 1, D01 X9R7, Ireland

+49 800-723-6202 cs@lepro.de

Manufacturer information: LE Innovation Limited, ROOM S032, 2/F, THE CAPITAL, 61-65 CHATHAM

ROAD SOUTH, TSIM SHA TSUI, KOWLOON,

SIMPLIFIED EU DECLARATION OF CONFORMITY

LE Innovation Limited hereby declares that the type of radio device

Lepro E1-60 outdoor lamp complies with Directive 2014/53/EU. The full

text of the EU declaration of conformity is available at the following

website: <https://files.innpro.pl/lepro>

Manufacturer address: ROOM S032, 2/F, THE CAPITAL, 61-65 CHATHAM ROAD

SOUTH, TSIM SHA TSUI, KOWLOON

Radio frequency: 2412 MHz–2472 MHz (Wi-Fi)

2402 MHz–2480 MHz (Bluetooth)

Maximum radio frequency power: 20 dBm

Environmental protection

Waste electrical and electronic equipment marked in accordance with the European Union directive must not be

placed together with other municipal waste. It is subject to selective collection and recycling at designated points. By ensuring its proper disposal, you prevent potential negative consequences for the natural environment and human health. The collection system for waste equipment complies with locally applicable environmental regulations regarding waste disposal. Detailed information on this can be obtained from the municipal office, waste management facility, or the store where the product was purchased. The product meets the requirements of the so-called New Approach directives of the European Union (EU), concerning issues related to safety of use, health protection, and environmental protection, specifying hazards that should be detected and eliminated. This document is a translation of the original user manual created by the manufacturer. Detailed information about the distributor/manufacturer warranty conditions is available at the website <https://serwis.innpro.pl/gwarancja>

The product should be regularly maintained (cleaned) by the user or through specialized service points at the user's cost and scope. In the absence of information about necessary maintenance or service actions in the user manual, the physical condition of the product should be assessed regularly, at least once a week, for deviation from that of a physically new product.

In the event of detecting or identifying any deviation, urgent maintenance (cleaning) or servicing steps must be taken. Failure to perform proper maintenance (cleaning) and to respond when a deviation is detected may lead to permanent damage to the product. The warranty provider is not responsible for damages resulting from neglect. Importer: INNPRO Robert Błędowski sp. z o.o. ul. Rudzka 65c 44-200 Rybnik, Poland tel. +48 533 234 303 hurt@innpro.pl www.innpro.pl